Calhoun: The NPS Institutional Archive

DSpace Repository

Theses and Dissertations 1. Thesis and Dissertation Collection, all items

1971-06

Fourier analysis of experimental finite-amplitude standing waves

Winn, James Richard.

Monterey, California ; Naval Postgraduate School

http://hdl.handle.net/10945/15728

Downloaded from NPS Archive: Calhoun

Calhoun is the Naval Postgraduate School's public access digital repository for research materials and institutional publications created by the NPS community. Calhoun is named for Professor of Mathematics Guy K. Calhoun, NPS's first appointed -- and published -- scholarly author.

Dudley Knox Library / Naval Postgraduate School
411 Dyer Road / 1 University Circle
Monterey, California USA 93943

http://www.nps.edu/library

FOURIER ANALYSIS OF EXPERIMENTAL FINITE-AMPLITUDE STANDING WAVES

James Richard Winn

United States
Naval Postgraduate School

THESIS

FOURIER ANALYSIS OF EXPERIMENTAL FINITE-AMPLITUDE STANDING WAVES

by

James R. Winn

Thesis Advisor: J. V. Sanders

June 1971

Approved for public release; distribution unlimited.

T139961

Fourier Analysis of Experimental Finite-amplitude Standing Waves

by

James Richard Winn
Lieutenant, United States Navy
B.S.E.E., University of Washington, 1964

Submitted in partial fulfillment of the
requirements for the degree of

MASTER OF SCIENCE IN PHYSICS

from the

NAVAL POSTGRADUATE SCHOOL
June 1971

ABSTRACT

Finite-amplitude standing waves in air at ambient conditions contained in a rigid-walled cylindrical tube with a large length-to-diameter ratio were experimentally investigated. The pressure waveform at the end of the tube was digitized and Fourier analyzed on an IBM 360 digital computer. Amplitudes and phases were obtained for all harmonics with amplitudes greater than 1% of the fundamental for strength parameters from 0.25 to 1.00 and for frequency parameters from -0.8 to 2.0. The strength and frequency parameters are defined as MbQ and $2\Delta f/\Delta f_{\frac{1}{2}}$ respectively, where M is the Mach number of fundamental, b the nonlinearity parameter, Q the quality factor of the resonator, Δf the frequency away from fundamental resonance, and $\Delta f_{\frac{1}{2}}$ the band width at the half-power points. When these results are compared to the theoretical model of Coppens and Sanders, it is seen that while the theory accurately predicts the magnitude and shape of the harmonic content, it consistently underestimates the frequency at which each harmonic peaks. In addition, the theory fails to predict, except qualitatively, the phase angles.

TABLE OF CONTENTS

I. INTRODUCTION -- 5

II. EXPERIMENTAL CONSIDERATIONS ----------------------- 9

  A. APPARATUS -- 9

  B. MICROPHONE CALIBRATION ----------------------- 10

  C. MICROPHONE OUTPUT AND STRENGTH PARAMETER ----- 12

  D. ATTENUATION CONSTANT -------------------------- 12

  E. FREQUENCY PARAMETER --------------------------- 13

III. COMPUTER ANALYSIS -------------------------------- 14

  A. SAMPLE RATE ------------------------------------ 14

  B. THE DIGITAL COMPUTER PROGRAM ----------------- 15

  C. THE ANALOG TO DIGITAL CONVERSION ------------- 16

  D. SYSTEM TEST ------------------------------------ 18

IV. PROCEDURES -- 19

  A. PRERUN PROCEDURES ----------------------------- 19

  B. DATA TAKING PROCEDURES ----------------------- 20

V. RESULTS --- 21

APPENDIX A: A-D PROGRAM PARAMETERS AND OPTIONS -------- 23

APPENDIX B: FIGURES AND PLOTS ------------------------- 26

COMPUTER PROGRAMS -------------------------------------- 39

BIBLIOGRAPHY --- 50

INITIAL DISTRIBUTION LIST ------------------------------ 51

FORM DD 1473 --- 52

LIST OF FIGURES

1. Apparatus Block Diagram ---------------------------- 26
2. PI 6200 Dynamic Range ------------------------------ 27
3. Analog Patch Board --------------------------------- 28
4. Logic Patch Board ---------------------------------- 29
5. Test Signal Analysis ------------------------------- 30
6. Point Scatter -------------------------------------- 31
7. Harmonic Amplitudes SP = 0.25 ---------------------- 32
8. Harmonic Amplitudes SP = 0.50 ---------------------- 33
9. Phase Plot SP = 0.50 ------------------------------- 34
10. Harmonic Amplitudes SP = 0.75 --------------------- 35
11. Phase Plot SP = 0.75 ------------------------------ 36
12. Harmonic Amplitudes SP = 1.00 --------------------- 37
13. Phase Plot SP = 1.00 ------------------------------ 38

I. INTRODUCTION

Coppens and Sanders [1,2] have developed a one-dimensional, nonlinear wave equation with dissipative terms corresponding to those encountered in a rigid-walled closed tube with a large length-to-diameter ratio. An attenuation constant of the form

$$\alpha_n = \alpha_1/\sqrt{n}$$

is assumed, where α_n is the absorption coefficient associated with the frequency $n\omega$ which characterizes the wall losses, R is the radius of the tube and L is the length of the tube. With this additional loss mechanism the wave equation takes the form

$$\sum_{n=1}^{\infty} \left(\frac{\partial^2}{\partial x^2} - \frac{1}{C_o^2} \frac{\partial^2}{\partial t^2} + D_n \right) \cdot U_n = b \frac{\partial^2}{\partial x \partial t} \left(\frac{\partial \xi}{\partial x} \right)^2 ,$$

where

$b = (\gamma+1)/2 = (C_p/C_v+1)/2,$

$D_n = \delta_1 \left(\frac{1}{\omega n^{3/2}} \frac{\partial^3}{\partial x^2 \partial t} - \frac{1}{n^{1/2}} \frac{\partial^2}{\partial x^2} \right),$

$\delta_1 = \frac{2}{R} \left(\frac{\nu}{2\omega} \right)^{\frac{1}{2}} \left[1 + \frac{\gamma-1}{(Pr)^{\frac{1}{2}}} \right],$

γ = C_p/C_v the ratio of specific heats,

ν = kinematic viscosity,

Pr = Prandtl number,

ω = angular frequency of the fundamental,

n = harmonic number,

C_o = the thermodynamic speed of sound,

α_1 = absorption coefficient for the lowest frequency

and

U = particle velocity = $\frac{\partial \xi}{\partial t} + \sum_n U_n$.

To arrive at the above equation it was necessary to make the simplifying assumptions that the wall losses were much greater than the bulk losses and that the Mach number

$$M = P_1/\rho_o C_o^2$$

is much less than unity. P_1 is the peak value of the fundamental of the pressure at the rigid end of the tube.

A Fourier series solution of the form

$$\frac{P(x_1 t)}{\rho_o C_o^2} = M \sum_{n=1}^{\infty} R(n) \text{ Cos}\left[n\pi\left(1-\frac{x}{L}\right)\right] \text{Sin}(n\omega t+\phi n)$$

is assumed with the tube excited with a pressure distribution given by

$$P_1(x_1 t) = M\rho_o C_o^2 \text{ Cos}\pi(1-x/L)\text{Sin}\omega t.$$

When this solution was substituted directly into the nonlinear wave equation, the following set of algebraic equations resulted:

$$H_n\left[(\text{Cos}\theta_n)S_n - (\text{Sin}\theta_n)C_n\right]$$

$$= \frac{n}{2\ell_s}\left\{\frac{1}{2}\sum_{j=1}^{n-1}(S_{n-j}C_j+C_{n-j}S_j) - \sum_{j=1}^{\infty}(S_{n+j}C_j-S_{n+j}S_j)\right\}$$

and

$$H_n \left[(\mathrm{Cos}\,\theta_n) C_n + (\mathrm{Sin}\,\theta_n) S_n\right]$$

$$= \frac{n}{2\ell_s} \{\frac{1}{2} \sum_{j=1}^{n-1} (C_{n-j} C_j - S_{n-j} S_j)$$

$$- \sum_{j=1}^{\infty} (C_{n+j} C_j + S_{n+j} S_j)\},$$

where

$S_n = R_n \mathrm{Sin}\,\phi_n$, $C_n = R_n\,\mathrm{Cos}\,\phi_n$,

$\ell_s = 2/SP$,

$$\theta_n = \mathrm{Tan}^{-1} \left[\frac{1 - n^{-\frac{1}{2}} - 2\Delta\omega/\omega_r \delta_1}{n^{-\frac{1}{2}} t n \alpha_2/\alpha_1}\right]$$

$$= \mathrm{Tan}^{-1} [A/B]_1$$

$H_n = (A^2 + B^2)^{\frac{1}{2}}$,

α_2 = infinitesimal amplitude absorption coefficient in free space,

ω_r = angular frequency at resonance,

SP = strength parameter

$SP = Mbk/2\ _1 = P_1 bk/(2\rho_o C_o^2 \alpha_1)$

k = wave number

and

$\Delta\omega = \omega - \omega_r$.

These equations were then programmed for computer solution. For given values of $\Delta\omega$ and SP, the computer calculated values of P_n/P_1 and θ_n. At present, solutions have been found for strength parameters up to 0.75.

Previous investigations in this area have been carried out by Sanders [1,2] and Beech [3]. Both investigators examined the harmonic content of the pressure waveform at the rigid end of the tube near resonance conditions. Sanders employed a wave analyzer to obtain the frequency response for the first four overtones. Good agreement with theory was found but no phase information was obtained. Beech used photographic and graphical techniques to provide numerical analysis of pressure waveforms near resonance. Phase information, however, was obtained only for cases at resonance. Again good agreement with theory was obtained for cases approaching the onset of shock.

The present investigation examines both the harmonic content and phase relationships for strength parameters as high as 0.75. Again numerical methods were employed. Whereas the graphical techniques of Beech were used to generate 64 data equally spaced throughout the pressure wave form, the technique in this investigation employed analog-to-digital conversion by computer to provide better than 1000 data to represent the pressure waveform. With the pressure waveform digitized to such an extent, it was possible to obtain amplitude and phase information for all harmonics with amplitudes greater than one percent of the fundamental.

II. EXPERIMENTAL CONSIDERATIONS

A. APPARATUS

A block diagram of the experimental system used in this investigation is shown in Figure 1. Finite-amplitude standing waves were generated in air at ambient conditions contained within a tube six-feet long with an inner diameter of 2.250 in. and a wall thickness of 1.125 in. The air was excited at one end by a piston which was driven by an M-B Electronics Model EA 1500 exciter capable of a maximum no-load acceleration of 124g. The EA 1500 was driven by two M-B electronics Model 2120MB power amplifiers operating in parallel. The maximum attainable acceleration with the weight of the piston as load was about 50g. The frequency and power level were controlled by a General Radio Type 1161-AGC coherent decade frequency synthesizer. With this synthesizer it was possible to select frequency to better than 0.001 cycles/sec. (Monitoring the frequency with a Hewlett-Packard Model 521C frequency counter showed the frequency stability to be better than one part in 10 million.) The acceleration of the piston was determined by measuring the output an Endeveco Model 2215 accelerometer implanted within the piston. When the piston was withdrawn from the tube and driven in free air at the approximate experimental frequency and acceleration, the harmonic distortion was measured to be less than 0.3 percent. The other end of the

tube was capped with a thick plate which was securely bolted to the tube. The sound pressure level at the rigid end of the tube was detected with a 1/4-in. diameter Bruel and Kjaer Type 4136 condenser microphone mounted in the cap so that its diaphragm was flush with the end of the tube. The microphone response was flat to within ± 0.5 dB from 80 Hz to 20 kHz. The outputs of the microphone and accelerometer were monitored with Hewlett-Packard 400D vacuum-tube voltmeters. The microphone output also went to a Hewlett-Packard Model 302A wave analyzer so that the first two overtones could be monitored. The microphone output was recorded by a PI 6200 General Purpose Portable Instrumentation Tape Recorder. Recordings were made in the FM mode at a tape speed of 37.5 in/s so that the frequency response of the tape recorder was ± 1 dB from DC to 10 kHz. Although the signal was recorded at 37.5 in/s it was necessary when digitizing the signal to play back at a speed of 3.75 in/s. To insure that this change in tape speeds did not alter the recorded frequencies, a test signal was recorded at the higher speed and then played back at the slow speed. The two signals were observed on a dual trace oscilliscope where it was observed that the frequency of the test signal was 10.0 times that of the signal played back at 3.75 in. per second with no discernable drift between the two signals.

B. MICROPHONE CALIBRATION

Investigation of the standing waves at various strength parameters requires an absolute calibration of the microphone

system. The microphone system is defined here as the microphone, preamplifier and the equipment loaded onto the output of the preamplifier. The system sensitivity is defined as

$$S_m = V_m/P$$

where V_m is the peak voltage output of the preamplifier and P is the peak pressure at the microphone. Two methods were employed to determine S_m. The first and simplest used a Bruel and Kjaer Model 4220 pistonphone which produces a known sound pressure level at 250 Hz. The sensitivity was found to be $S_m = (-77.1 \pm 0.2)$dB re 1 volt/μbar, where the uncertainty is that inherent in the pistonphone specifications. The second method makes use of theoretical predictions by Coppens for small strength parameters as verified by Beech [3]. Coppens shows that at resonance the ratio of the peak pressure of the second harmonic to the square of the peak pressure of the fundamental is given by

$$P_2/P_1^2 = (\sqrt{2}\ \omega\beta)/(8\rho_o C_o^3 \alpha).$$

When the definition of sensitivity is substituted into the above equation the result is

$$S_m = (\beta\omega V_1^2)/(4\sqrt{2}\ \rho_o C_o^3 \alpha V_2).$$

S_m was then found by exciting the tube at resonance and measuring the fundamental and second-harmonic voltages. By this method $S_m = (-77.2 \pm 0.3)$dB re 1 volt/μbar where the uncertainty is due largely to the error in determining the attenuation constant.

C. MICROPHONE OUTPUT AND STRENGTH PARAMETER

In this investigation, where the pressure waveform was to be analyzed at various strength parameters, it was necessary to find a relationship between the strength parameter and the observable quantities. Using the equations

$$S_m = \text{SPL} + 21 \log\left(\frac{\nu}{.775}\right) + 72.0,$$

$$M = \frac{P_1}{\rho_o C_o^2} = \frac{P_1}{P_o} - \frac{P_o}{\rho_o C_o^2} = \text{SPL} - 197.0,$$

and

$$M = \frac{\text{SP}(2\alpha/K)}{b},$$

one can show that the rms value of the fundamental of the microphone output (v) is related to strength parameter and the attenuation constant by

$$v = 136.0\,\alpha \cdot \text{SP}.$$

The constant 136.0 is relatively insensitive to small temperature variations about room temperature.

D. ATTENUATION CONSTANT

The attenuation constant for infinitesimal amplitudes has been shown by Beech to be

$$\alpha_1 = \left(\frac{\pi}{C_o}\right) \Delta f,$$

where Δf is the frequency difference between the half power points on the resonance curve (taken for constant acceleration amplitude of the piston).

E. FREQUENCY PARAMETER

The frequency parameter is defined by

$$FP = 2\Delta\omega/\omega_r\delta_1,$$

where

$$\Delta\omega = \omega - \omega_r$$

and

$$\delta_1 = 2\alpha_1 C_o/\omega_r.$$

This frequency parameter is related to the experimental frequency increment (Δf_{ex}) by

$$\Delta f_{ex} = \Delta f \cdot FP/2,$$

where Δf is the frequency difference between the half power points of the infinitesimal resonance curve as used in calculating α_1 in this investigation Δf was found to be $1.15 \pm 0.01H_3$ so that

$$\Delta f_{ex} = 0.58\ FP.$$

III. COMPUTER ANALYSIS

A. SAMPLE RATE

Many computer programs exist which, when supplied with data points defining a periodic waveform, will give the Fourier coefficients. The first consideration, generally, is the number of data required per cycle. Theoretically this number should be at least twice the number of harmonics desired. However, the question of accuracy of the computer predictions of harmonic amplitudes arises immediately. As might be expected, the accuracy of the harmonics determined tails off faster as fewer samples per cycle are used. This then leads to the problem of first determining how many significant harmonics are desired. For finite-amplitude standing waves of large strength parameter the waveform qualitatively approaches a function whose harmonics content falls off inversely with harmonic number. If such a waveform is passed through amplifiers and storage devices before being analyzed, harmonics below a given amplitude will be lost in the inherent noise. The device in this investigation which was most seriously restrictive in this respect was the PI 6200 FM tape recorder. It was found that the dynamic range of this instrument was about 42 db which restricted the investigation to harmonics with amplitudes greater than about one percent of the fundamental. For a periodic ramp function this restriction occurs at about the 30th harmonic.

Determination of the number of samples per cycle to be used was based on the arbitrary criterion that the error in the 30th harmonic be less than 0.1 percent for an ideal ramp function. Applying several computer algorithms for determining Fourier coefficients to an ideal ramp function one finds that 1000 samples per cycle are required for the above accuracy.

B. THE DIGITAL-COMPUTER PROGRAM

The primary function of this program was to generate normalized Fourier coefficients for a periodic function given digitized data on a seven-track tape. Secondary to this, the program changed the form of the coefficients to $A(n) \text{Sin}(N\omega t + \phi(n)$ and computed $A(n)/A(1)$ for each harmonic. Optional functions provided by the program were the averaging of several periods of data to reduce the affects of random noise. An optional plot of the input data was available along with points reconstructed from the calculated Fourier coefficients. This plot provided a visual check on the input data and the computed coefficients.

The digitized data provided by the SDS 9300 were written on seven-track tape. However, the binary representation of numbers on the seven-track tape differs from those on the standard nine-track tape used by the IBM 360 system. To accomodate the seven-track tape, a conversion program (subroutine FORM) was used to convert the data. The converted data were not floating point but integers and required further conversion with the use of a scaling factor.

Prime consideration was given to the types of algorithms commonly used in generating Fourier coefficients. Two of the more widely used methods are the Cooley-Tukey [5] Fast Fourier transform and the recursive technique of Goertzel [4]. Both methods were tested for accuracy in predicting the coefficients of known waveforms. The two methods were found to be equal. One advantage of the Cooey-Tukey method is its minimal use of computer time. Its computation time is about an order of magnitude less than that required by the Goertzel method. However, when this time saving is compared with the overall required computer time for analysis the advantage diminishes. The final consideration and, in the end the most important, was the flexibility in using data. The Cooley-Tukey method required an integer power-of-two number of points. To be able to satisfy this condition along with the requirement for 1000 or more samples per cycle complicated the digitizing process. The Goertzel method required only an odd number of samples and for this reason was used in the computer program.

C. THE ANALOG TO DIGITAL CONVERSION (A-D)

The conversion of the analog data was accomplished with the use of a hybrid computer consisting of the SDS 9300 high-speed digital computer and the Ci 5000 general-purpose analog computer. Use of the system for A-D conversion requires a FORTRAN program for the SDS 9300 and properly constructed analog and logical patch boards for the Ci 5000. In addition, several peripheral equipments are required.

These are the card reader, magnetic tape transport, line printer and, if desired, a pen recorder.

Aside from the question of sampling, which was determined earlier, the important question in the A-D conversion is accuracy. The clock in the computer is accurate to one part in 100 million, well within any accuracy requirements. The A-D converter is designed to accept signals between ± 100 volts and divide this interval into 16,384 parts providing a resolution of 12.2 mV. For a properly amplified analog signal, the dynamic range of the A-D converter is much greater than the PI 6200 tape recorder.

The analog patch board (Figure 3), as used for A-d conversion, served to amplify the analog signal prior to conversion and distributed the signal to the converter and oscilliscope. Additionally, a patch was provided linking the Digital-to-Analog converter with a pen recorder. This additional function is explained in detail in the procedures section.

The logic patch board (Figure 4), had three functions. The first provided a sampling frequency (10,000 Hz) to the A-D converter. This frequency represents the approximate maximum sampling rate allowed. Since the approximate resonant frequency of the tube was 94 Hz it was necessary to play back signals from the PI 6200 at one tenth the recorded speeds to acquire the desired number of samples per cycle. The second function provided a triggering voltage through an external switch (DS-1) which was used to start the data

conversion process. Associated with this function is an externally controlled delay (DF00) which insured that the triggering voltage remained on long enough for one set of data (one record) to be written on the seven-track tape. The last function provided another triggering voltage through an external switch (DS-2). When the last record was to be written on tape switch DS-2 was turned on while switch DS-2 was triggered.

D. SYSTEM TEST

Prior to analyzing experimental data, it was necessary to test the entire system process of A-D conversion and computer analysis. The results of this test for a ramp function is shown in Figure 5.

IV. PROCEDURES

A. PRERUN PROCEDURES

Beech pointed out that the resonant frequency of the tube changed by 0.16 Hz for each degree centigrade of temperature change. To minimize this affect, all data gathering runs were made during the evening hours when the room temperature remained relatively constant for several hours. Typical resonant frequency variations during these hours were of the order of 0.01 Hz per hour. Several hours prior to taking data the equipment was turned on and allowed to stabilize. During this warmup period, the PI 6200 tape recorder was calibrated to insure that the FM system was properly aligned and to insure that the signals being recorded were not overdriving the tape recorder preamplifier and thereby introducing unwanted signal distortion. Next, the alignment of the piston in the free end of the tube was checked by observing the output of the accelerometer on an oscilloscope and measuring, with a wave analyzer, the second- and third-harmonic content. If necessary, the harmonic content could be reduced by carefully adjusting the alignment of the piston so that the distortion from any harmonic was less than 2 percent. To minimize leakage of sound from the tube, the piston was fitted with an "O" ring and lubricated. The harmonic distortion introduced by the piston was sensitive to the type of lubricant

used. It was found that a light turbine oil minimized the distortion while providing an adequate seal.

Just prior to taking each set of data, it was necessary to determine the resonant frequency and the attenuation constant. For this measurement the piston was excited at a constant value of acceleration low enough so that the strength parameter at resonance was less than 0.03. From the frequency difference between the half power points, the attenuation constant was determined. The resonance frequency was taken to lie half way between the half power points.

B. DATA TAKING PROCEDURE

Corresponding to the desired strength parameter was a given value of the pressure fundamental as shown earlier. With the piston excitation set to the proper level to keep the pressure fundamental constant, data were recorded at 0.1 Hz intervals for twenty frequencies from 0.6 Hz below resonance to 1.3 Hz above. At each frequency, the signals from the microphone and accelerometer were recorded on the PI 6200 at high speed (37.5 in/s) for about 10 seconds (30 ft.), and the second-harmonic amplitude of the pressure was noted to be later compared with the computer analysis. Since the taking of an entire set of data at one strength parameter required from 30 minutes to an hour, at the end of the run it was necessary to check the resonant frequency and attenuation constant to insure that the variation in resonant frequency was substantially less than one frequency interval (0.1 Hz) and that the change in attenuation constant was less than one percent.

The theoretical predictions (8) are compared with the experimental results in Figures 6 through 13 for each value of strength parameter, plots are shown of the harmonic amplitude vs. frequency parameter and of the phase difference between consecutive harmonics vs. inverse harmonic number. Figure 6 shows the actual data obtained for three different experimental runs. The degree of scatter is a demonstration of the excellent reproducibility of the results. Both experimental and theoretical results are limited to harmonics with amplitude greater than 1% of the fundamental.

In comparing the experimental values of the harmonic amplitudes with the theoretical predictions for a strength parameter of 0.25 it is seen that the agreement is fairly good but that there does seem to be a slight systematic difference. The corresponding curves for higher strength parameters display this difference to a more marked degree. It is seen that the experimental results peak at about the predicted values of $P_{(n)}/P_{(1)}$ and that the shape of the curve for each harmonic is about as predicted. However, the experimental results peak at a value of frequency parameter significantly greater than predicted and this difference increases with harmonic number. It is interesting to note that at the frequency of maximum distortion of the pressure waveform (at approximately FP = 0.5) theory accurately predicts the harmonic amplitudes.

The comparison between the experimental and theoretical phase angles displays an even greater discrepancy. While

values of $\phi_n - \phi_{n-1}$ do seem to be linearly related to 1/n, the values for the second harmonic are greatly different and the slopes of the experimental curves are significantly greater than predicted.

In conclusion, it appears that while the present theoretical model is able to predict the magnitude and shape of the harmonic content of the distorted waveform, it consistently underestimates the frequency at which each harmonic peaks. This underestimation increases with harmonic number and strength parameter. In addition, it fails to predict, except qualitatively, the phase relations in the distorted wave.

APPENDIX A

THE A-D PROGRAM PARAMETERS AND OPTIONS

The purpose of this program was to convert up to four channels of analog data into a series of digital points on seven-track magnetic tape. The program had several input parameters which had to be provided to the computer via the teleprinter after the FORTRAN program had been read into the system.

NSAMP (input 1.) was an integer which corresponded to the number of data or samples to be taken from each channel. For this investigation a sampling rate of 10 kHz was used and NSAMP was chosen to span one cycle of the input waveform.

NCHAN (input 2.) was an integer which specified the number of channels of analog data being converted.

NREC (input 2.) specified how many records were to be written on tape each time sampling was initiated. A record was defined as the data set corresponding to the product of NCHAN and NSAMP. Because of the high sampling rate used it was necessary to set this value to 1.

ITAPE (input 4.) designated which magnetic-tape transport held the seven-track tape. The integer used here had to correspond that selected on the "unit select" switch on the particular tape unit used.

NDEL (input 5.) determined how rapidly the data on the seven-track tape was read back when using program option 7.

An example of the input parameters as typed on the teleprinter might be

NREC = 1, NSAMP = 1000, NCHAN = 3, ITAPE = 1,
NDEL = 20* (carriage return).

The control symbol * indicated to the computer that the input parameters had been set. Care was taken when choosing NSAMP and NCHAN to insure that their product did not exceed the first dimension of IBUF found in the first FORTRAN program statement.

When the parameter list had been given the teleprinter responded with

"OPTION = (I1)".

The computer was then given a one-digit number corresponding to the list of available options.

RESTART (option 1.) was used whenever any one or all of the input parameters was to be changed.

GO (option 2.) was used when analog to digital conversion was to be done. Upon receiving this option the computer awaited the initiating trigger from switch DS-1 to start the actual conversion process. Each trigger from DS-1 caused one record of data to be written on tape. When a sufficient number of records were written, DS-1 was triggered with DS-2 in the "up" position. This caused the last record to be written followed by a teleprinter response

"OPTION = (I1)".

END OF FILE (option 3.) was used to put a mark on the tape to separate or isolate groups of records. Groups of records separated by END OF FILE marks are called files.

SKIPFILES (option 5.) were used when files already on tape were to be skipped over. When used, a four-digit number was given the computer to specify the number of files to be skipped.

LIST ONE RECORD (option 6.) was used in reading data from the seven-track tape. Use of this option caused data written on tape to be written on the page printer after having specified the number of data to print.

PLOT ONE RECORD (option 7.), when called, caused one record to be read from the tape, converted to an analog signal, and fed to terminals T420 through T423 on the analog board (corresponding to channels 1 through 4). The signal could then be monitored on various recording devices. Because of the short duration of the signal it was best displayed on the available pen recorder whose input terminals are found on the analog board (Figure 3). The time base of the signal returned from the tape could be lengthened or shortened by varying the value of the input parameter NDEL.



Figure 1. Apparatus.



Figure 2. PI 6200 Dynamic Range.



TYPICAL ANALOG PATCH FOR ONE CHANNEL WITH A GAIN OF 50

Figure 3. Analog Patch Board.



Figure 4. Logic Patch Board.



Figure 5. Test Signal Analysis.



Figure 6. Point Scatter.



Figure 7. Harmonic Amplitudes SP = 0.25.



Figure 8. Harmonic Amplitudes SP = 0.50.



Phase differences for constant D_p

Figure 9. Phase Plot SP = 0.50.



Figure 10. Harmonic Amplitudes SP = 0.75.



Figurell. Phase Plot SP = 0.75.



Figure 12. Harmonic Amplitudes SP = 1.00.



Figure 13. Phase Plot SP = 1.00

A. DIGITAL

```
//CONVERT EXEC FORTCALG,REGION.GO=130K,TIME.GO=1                        WIN00020
//FORT.SYSIN DD *                                                       WIN00030
      REAL LABEL/4H    /                                                WIN00040
      REAL*8 A(101),B(101),Y(1100),ITITLE(12),SCALE                     WIN00050
      DIMENSION INDATA(3600),DATA(1100,3),YY(1100),C(1100),             WIN00060
     1KNEW(4),X(1100)                                                   WIN00070
      READ(5,15) (ITITLE(I),I=1,12)                                     WIN00080
   15 FORMAT(6A8)                                                       WIN00090
C***********************************************************************WIN00100
C     SET THE VALUE OF STRENGTH PARAMETER.                              WIN00110
      SP=0.75                                                           WIN00120
C     SET THE NUMBER OF CHANNELS ON TAPE                                WIN00130
      NC=1                                                              WIN00140
C     SET THE NUMBER OF HARMONICS TO BE CALCULATED.                     WIN00150
      NH=10                                                             WIN00160
C     SET NDRAW TO 1 FOR CALCOMP PLOT.                                  WIN00170
      NDRAW=0                                                           WIN00180
C     SET NREC TO THE NUMBER OF RECORDS TO BE AVERAGED.                 WIN00190
C***********************************************************************WIN00200
      NREC=1                                                            WIN00210
      FACTOR=100.0/(2**31-1)                                            WIN00220
      REWIND 2                                                          WIN00230
      PI=3.141592653589793                                              WIN00240
  110 NCASE=0                                                           WIN00250
C     SET THE INITIAL RECORD COUNT AND BEGIN A NEW CASE.                WIN00260
  111 J=0                                                               WIN00270
      NCASE=NCASE+1                                                     WIN00280
      DO 112 I=1,NC                                                     WIN00290
  112 KNEW(I)=0                                                         WIN00300
C     PROCESS A NEW RECORD                                              WIN00310
C     STEP THE RECORD COUNT AND ZERO THE CHANNEL NUMBER                 WIN00320
    1 J=J+1                                                             WIN00330
      K=0                                                               WIN00340
      NSAMP=1090                                                        WIN00350
      NP=NC*NSAMP                                                       WIN00360
C     READ THE TAPE                                                     WIN00370
      READ(2,2,END=12,ERR=10)  (INDATA(I), I=1,NP)                      WIN00380
    2 FORMAT(109(10A4))                                                 WIN00390
C     READ IN THE PARTICULAR FREQUENCY AND SAMPLE COUNT FOR THIS CASE.  WIN00400
      READ(5,555) NSAMP,FREQ                                            WIN00410
  555 FORMAT(I4,F8.1)                                                   WIN00420
C     CONVERT THE SEVEN TRACK TAPE FOR USE IN THE IBM 360 SYSTEM        WIN00430
```

```
      CALL FORM(INDATA)                                                 WIN00440
C     PROCESS A NEW CHANNEL                                             WIN00450
   35 CONTINUE                                                          WIN00460
C     STEP THE CHANNEL COUNT                                            WIN00470
      K=K+1                                                             WIN00480
C     CONVERT THE DATA TO DECIMAL                                       WIN00490
      TSCALE=0.0                                                        WIN00500
      DSCALE=0.5                                                        WIN00510
      DO 4 I=1,NSAMP                                                    WIN00520
C     ZERO THE DATA VECTOR BEFORE ADDING THE RECORDS TOGETHER.          WIN00530
      IF(J.EQ.1) DATA(I,K)=0.0                                          WIN00540
      X(I)=INDATA(NC*(I-1)+K)*FACTOR                                    WIN00550
C     FIND THE NEGATIVE GOING AXIS CROSSING POINT                       WIN00560
      IF(ABS(X(I)).GT.DSCALE) GO TO 4                                   WIN00570
      IF(I.GT.10) GO TO 405                                             WIN00580
      DHP     =INDATA(NC*(I+8)+K)*FACTOR                                WIN00590
      IF(DHP.GT.0.0) GO TO 4                                            WIN00600
      GO TO 404                                                         WIN00610
  405 DLP     =INDATA(NC*(I-9)+K)*FACTOR                                WIN00620
      IF(DLP.LT.0.0) GO TO 4                                            WIN00630
  404 DSCALE=ABS(X(I))                                                  WIN00640
C     KEEP TRACK OF NEWI TO USE IN FINDING THE PHASE DIFFERENCE         WIN00650
C     BETWEEN CHANNELS.                                                 WIN00660
      NEWI=I                                                            WIN00670
    4 IF(ABS(X(I)).GT.TSCALE) TSCALE=ABS(X(I))                          WIN00680
      KNEW(K)=KNEW(K)+NEWI                                              WIN00690
C     REORGANIZE THE INPUT DATA SO THAT THE NEGATIVE GOING CROSSING     WIN00700
C     POINT IS THE FIRST DATA POINT.                                    WIN00710
      DO 44 I=1,NSAMP                                                   WIN00720
      IF(I.LT.NEWI) GO TO 444                                           WIN00730
      DATA(I-NEWI+1,K)=X(I)+DATA(I-NEWI+1,K)                            WIN00740
      GO TO 44                                                          WIN00750
  444 DATA(NSAMP-NEWI+1+I,K)=X(I)+DATA(NSAMP-NEWI+1+I,K)                WIN00760
   44 CONTINUE                                                          WIN00770
C     DETERMINE IF MORE RECORDS ARE TO BE READ BEFORE PROCESSING.       WIN00780
      IF(K.LT.NC) GO TO 35                                              WIN00790
      IF(J.LT.NREC) GO TO 1                                             WIN00800
C***********************************************************************WIN00810
C                                                                       WIN00820
C     ONE CASE HAS BEEN READ IN TO THE DATA VECTOR AND IS READY TO      WIN00830
C     BE PROCESSED AT THIS POINT.                                       WIN00840
C                                                                       WIN00850
C***********************************************************************WIN00860
C     ZERO THE CHANNEL COUNT                                            WIN00870
      K=0                                                               WIN00880
C     SET THE CHANNEL COUNT AND THE INITIAL SCALE AND EXTRACT THE DATA  WIN00890
C     FOR THE CURRENT CHANNEL NUMBER.                                   WIN00900
   53 K=K+1                                                             WIN00910
```

```
      SCALE=0.01                                                        WIN00920
      DO 55 I=1,NSAMP                                                   WIN00930
      Y(I)=DATA(I,K)                                                    WIN00940
   55 IF(DABS(Y(I)).GE.SCALE) SCALE=DABS(Y(I))                          WIN00950
C     LABEL THE CHANNEL NUMBER                                          WIN00960
      WRITE(6,45) NCASE,K                                               WIN00970
   45 FORMAT('1','CASE NUMBER',I3,6X,'CHANNEL NUMBER',I3,///)           WIN00980
C     FIND THE FOURIER COEFFICIENTS WITH SUBROUTINE FOX.                WIN00990
      CALL FOX(Y   ,NSAMP,NH,A,B,IER,SCALE)                             WIN01000
      WRITE(6,6)                                                        WIN01010
C     LABEL THE OUTPUT DATA                                             WIN01020
    6 FORMAT(1X,'HARMONIC',7X,'A(N)',10X,'B(N)',14X,'C(N)',10X,'PHI(N)',WIN01030
     110X,'A(N)/A(1)')                                                  WIN01040
      C(1)=A(1)                                                         WIN01050
C     CHANGE THE COEFFICIENTS TO THE FORM....A(N)SIN(NWT+PHI(N)))       WIN01060
      DO 8 I=1,NH                                                       WIN01070
      IF(I.LT.2) GO TO 7                                                WIN01080
      C(I)=DSQRT(A(I)**2+B(I)**2)                                       WIN01090
      PHI=DATAN2(A(I),B(I))                                             WIN01100
    7 CONTINUE                                                          WIN01110
      IF(I.EQ.1) PHI=0.0                                                WIN01120
C     NUMBER THE HARMONICS                                              WIN01130
      N=I-1                                                             WIN01140
      RATIO=0.0                                                         WIN01150
      IF(I.EQ.1) GO TO 8                                                WIN01160
C     WRITE THE OUTPUT DATA                                             WIN01170
      RATIO=C(I)/C(2)                                                   WIN01180
    8 WRITE(6,9)(N,A(I),B(I).C(I),PHI,RATIO)                            WIN01190
    9 FORMAT(I4,5F16.4)                                                 WIN01200
C     FIND THE PHASE DIFFERENCE BETWEEN THE PRESSURE (CH1) AND THE      WIN01210
C     ACCELEROMETER(CH2)                                                WIN01220
      IF(K.EQ.2)DEL= IABS(KNEW(1)-KNEW(2))*360.0/(NREC*NSAMP)           WIN01230
C     DETERMINE THE NUMBER OF POINTS TO BE USED IN CALL DRAW SUBROUTINE WIN01240
      KK= 1+NSAMP/900                                                   WIN01250
      IF(NDRAW.EQ.0) KK=1                                               WIN01260
C     DETERMINE THE POINTS TO BE PLOTTED FROM THE ORIGINAL NORMALIZED,  WIN01270
C     SHIFTED DATA AND CREAT AN ADDITIONAL SET OF POINTS FROM           WIN01280
C     THE FOURIER COEFFICIENTS.                                         WIN01290
      L=1                                                               WIN01300
      SQ=0.0                                                            WIN01310
      Q=0.0                                                             WIN01320
      DO 95 I=1,NSAMP,KK                                                WIN01330
      DD=0.0                                                            WIN01340
      DO 97 KH=1,NH                                                     WIN01350
      THETA=(KH-1)*((I)*2.0*PI/FLOAT(NSAMP))                            WIN01360
   97 DD=DD+A(KH)*COS(THETA)+B(KH)*SIN(THETA)                           WIN01370
C     RECONSTRUCTED DATA ORDINATES, X AXIS POINTS, AND ORIGINAL         WIN01380
C     ORDINATES                                                         WIN01390
```

```
      C(L)=DD                                                           WIN01400
      X(L)=360.0*FLOAT(I-1)/FLOAT(NSAMP-1)                              WIN01410
      YY(L)=Y(I)/ SCALE                                                 WIN01420
C     CALCULATE THE AVERAGE DIFFERENCE BETWEEN TNE INPUT POINTS AND     WIN01430
C     THE RECONSTRUCTED POINTS.  DO THE SAME FOR THE RMS ERROR.         WIN01440
      DELTA=C(L)-YY(L)                                                  WIN01450
      Q=DELTA+Q                                                         WIN01460
      SQ=DELTA**2+SQ                                                    WIN01470
C     DETERMINE THE NUMBER OF POINTS IN THE PLOTP SUBROUTINE            WIN01480
   95 L=L+1                                                             WIN01490
      AQ=Q/FLOAT(L-1)                                                   WIN01500
      RMS =SQRT(SQ/FLOAT(L-1))                                          WIN01510
      WRITE(6,950) AQ,RMS,FREQ,NSAMP                                    WIN01520
  950 FORMAT('0','AVERAGE DIFFERENCE',F10.6,//,' RMS ERROR',F7.4,//,    WIN01530
     2' FREQUENCY',F7.2,//,' NUMBER OF SAMPLES',I6)                     WIN01540
C     CORRECT THE NUMBER OF PLOT POINTS                                 WIN01550
      L=L-1                                                             WIN01560
C                                                                       WIN01570
C     PLOT ON ONE GRAPH THE ORIGINAL DATA AND THE RECONSTRUCTED DATA    WIN01580
C     FOR EACH CHANNEL.                                                 WIN01590
C     TO SCALE THE PLOTP ROUTINE SELECT TWO POINTS AND SET THEM         WIN01600
C     TO THE DESIRED EXTREMUM VALUES.                                   WIN01610
      NDRAW=0                                                           WIN01620
      IF(NDRAW.EQ.0) GO TO 91                                           WIN01630
      ITITLE(6)=SP                                                      WIN01640
      ITITLE(9)=FREQ                                                    WIN01650
      ITITLE(11)=NSAMP                                                  WIN01660
      CALL DRAW(L,X,YY,1,0,LABEL,ITITLE,60.0,0.4,3,0,2,2,6,6,1,LAST)    WIN01670
      CALL DRAW(L,X,C,3,0,LABEL,ITITLE,60.0,0.4,3,0,2,2,6,6,1,LAST)     WIN01680
   91 CONTINUE                                                          WIN01690
      YY(1)=1.2                                                         WIN01700
      YY(1+120*KK)=-1.2                                                 WIN01710
      CALL PLOTP(X,YY,L,1)                                              WIN01720
      CALL PLOTP(X,C,L,3)                                               WIN01730
C                                                                       WIN01740
C                                                                       WIN01750
      IF(K.NE.2) GO TO 99                                               WIN01760
      WRITE(6,98) SP,DEL                                                WIN01770
   98 FORMAT('0','STRENGTH PARAMETER=',F6.3,'PHASE=',F7.2)              WIN01780
C     CHECK THE CHANNEL NUMBER AND DETERMINE IF ANOTHER CHANNEL IS      WIN01790
C     TO BE PROCESSED OR A NEW CASE IS TO BE READ.                      WIN01800
   99 CONTINUE                                                          WIN01810
      IF(K.EQ.NC) GO TO 111                                             WIN01820
      GO TO 53                                                          WIN01830
   10 WRITE(6,11) J                                                     WIN01840
   11 FORMAT ('0',5X,'READ ERROR, RECORD NO.',I3)                       WIN01850
      GO TO  1                                                          WIN01860
   12 WRITE(6,13) J                                                     WIN01870
```

```
 13 FORMAT ('0',5X,'END OF TAPE, RECORD NO.=',I3)                WIN01880
 14 CONTINUE                                                     WIN01890
    STOP                                                         WIN01900
    END                                                          WIN01910


    SUBROUTINE FOX(FNT , NSAMP,M,A,B,IER,SCALE)                  WIN01920
    IMPLICIT REAL*8(A-H),REAL*8(O-Z)                             WIN01930
    DIMENSION A(1),B(1),FNT(1)                                   WIN01940
    IER=0                                                        WIN01950
    N=(NSAMP-1)/2                                                WIN01960
 20 IF(M) 30,40,40                                               WIN01970
 30 IER=2                                                        WIN01980
    RETURN                                                       WIN01990
 40 IF(M-N) 60,60,50                                             WIN02000
 50 IER=1                                                        WIN02010
    RETURN                                                       WIN02020
 60 AN=N                                                         WIN02030
    MP1 = M+1                                                    WIN02040
    DZ = 0.D0                                                    WIN02050
    D1 = 1.D0                                                    WIN02060
    D2 = 2.D0                                                    WIN02070
    COEF = D2/(D2 * AN + D1)                                     WIN02080
    CONST = 3.141592653589793 * COEF                             WIN02090
    S1 =  DSIN(CONST)                                            WIN02100
    C1 =  DCOS(CONST)                                            WIN02110
    C = D1                                                       WIN02120
    S = DZ                                                       WIN02130
    J=1                                                          WIN02140
    FNTZ=FNT(1)/SCALE                                            WIN02150
 70 U2 = DZ                                                      WIN02160
    U1 = DZ                                                      WIN02170
    I=2*N+1                                                      WIN02180
 75 U0=FNT(I)/SCALE+D2*C*U1-U2                                   WIN02190
    U2=U1                                                        WIN02200
    U1=U0                                                        WIN02210
    I=I-1                                                        WIN02220
    IF(I-1) 80,80,75                                             WIN02230
 80 A(J)=COEF*(FNTZ+C*U1-U2)                                     WIN02240
    B(J)=COEF*S*U1                                               WIN02250
    IF(J-(M+1)) 90,100,100                                       WIN02260
 90 Q=C1*C-S1*S                                                  WIN02270
    S=C1*S+S1*C                                                  WIN02280
    C=Q                                                          WIN02290
    J=J+1                                                        WIN02300
    GO TO 70                                                     WIN02310
100 A(1) = A(1) / D2                                             WIN02320
    RETURN                                                       WIN02330
```

```
      END                                                               WIN02340
//ASM.SYSIN  DD   *                                                     WIN02360
FORM     START 0                                                        WIN02370
         STM   14,12,12(13)                                             WIN02380
         BALR  6,0                                                      WIN02390
         USING *,6                                                      WIN02400
         USING DATA,7                                                   WIN02410
         SR    7,7                                                      WIN02420
         L     11,=F'1090'                                              WIN02430
         L     12,0(1)                                                  WIN02440
LOOP     L     2,NUM(12)                                                WIN02450
         LR    3,7                                                      WIN02460
         SRDL  2,6                                                      WIN02470
         SRL   2,2                                                      WIN02480
         SRDL  2,6                                                      WIN02490
         SRL   2,2                                                      WIN02500
         SRDL  2,6                                                      WIN02510
         SRL   2,2                                                      WIN02520
         SRDL  2,6                                                      WIN02530
         ST    3,NUM(12)                                                WIN02540
         LA    12,4(12)                                                 WIN02550
         BCT   11,LOOP                                                  WIN02560
         LM    2,12,28(13)                                              WIN02570
         MVI   12(13),X'FF'                                             WIN02580
         BCR   15,14                                                    WIN02590
DATA     DSECT                                                          WIN02600
NUM      DS    1F                                                       WIN02610
         END                                                            WIN02620
//GO.FT02F001 DD UNIT=OCO,VOL=SER=WINN,LABEL=(6,NL),                    WIN02640
//       DISP=(OLD,KEEP),DCB=(DEN=1,RECFM=F,BLKSIZE=4360)               WIN02650
//GO.SYSIN  DD *                                                        WIN02660
J.R. WINN 1542   STRENGTH PARAMETER=                                    WIN02670
FREQUENCY=                                SAMPLES                       WIN02680
1063 94.1                                                               WIN02690
1063 94.1                                                               WIN02700
1063 94.1                                                               WIN02710
1055 94.8                                                               WIN02720
1055 94.8                                                               WIN02730
1055 94.8                                                               WIN02740
1065 93.9                                                               WIN02750
1065 93.9                                                               WIN02760
1065 93.9                                                               WIN02770
1051 95.2                                                               WIN02780
1051 95.2                                                               WIN02790
1051 95.2                                                               WIN02800
1059 94.5                                                               WIN02810
1059 94.5                                                               WIN02820
1059 94.5                                                               WIN02830
```

B. ANALOG CONVERSION

```
      DIMENSION IBUF(2048,2), LOCB(-1'1), MAXBS(-1'1)
      INTEGER RECNUM
      NAMELIST NREC, NSAMP, NCHAN, ITAPE,NDEL
1     INPUT(101)
      LOCB(-1)=LOCF(IBUF(1,1))
      LOCB(1)=LOCF(IBUF(1,2))
      NWORDS=NSAMP*NCHAN
      MAXBS(-1)=LOCB(-1)+NWORDS-1
      MAXBS(1)=LOCB( 1)+NWORDS-1
      IF(SENSE SWITCH 6)2,15
2     NB=1
      IND=0
      RECNUM=0
      NEWBUF=LOCB(1)
      MAXB=MAXBS(-1)
      CALL ADSTART(NCHAN,LOCB(-1),NEWBUF,MAXB,RECNUM,11S)
      MAXB=MAXBS(1)
3     IF(TEST(1).GT.0)GO TO 3
      CALL ENABLE
5     CONTINUE
10    GO TO 5
11    IF(IND.EQ.1)GO TO 90
      IF(TEST(1).GT.0.OR.RECNUM.GE.NREC)CALL DISABLE
      NB=-NB
      NEWBUF=LOCB(NB)
      MAXB=MAXBS(NB)
      IND=1
      CALL BUFFEROUT(ITAPE,1,IBUF(1,(3+NB)/2),NWORDS,IND)
      IF(TEST(1).LT.0.AND.RECNUM.LT.NREC)GO TO 5
      CALL ADSTOP
X     CALL PROCESS(IBUF,NSAMP,NCHAN,2S)
      OUTPUT(101)RECNUM
15    OUTPUT(101)-OPTION=(I1)-
      READ(101,100)NOPT
100   FORMAT(I1)
      GO TO(1,2,30,40,50,60,70)NOPT
30    ENDFILE(ITAPE)
      OUTPUT(101)-EOF-
      GO TO 15
40    REWIND(ITAPE)
      GO TO 15
50    OUTPUT(101)-SKIPFILES=(I4)-
      READ(101,101)NF
101   FORMAT(I4)
      DO 55 I=1,NF
51    CALL BUFFERIN(ITAPE,1,IBUF(1,1),1,IND)
52    IF(IND.LT.2)GO TO 52
      IF(IND.NE.3)GO TO 51
```

```
55    CONTINUE
      OUTPUT(101)NF
      GO TO 15
60    OUTPUT(101)-NUMWORDS TO LIST=(I4)-
      READ(101,101)NW
      WRITE(101,105)NW,NCHAN
105   FORMAT(- WRITE - I4 - WORDS, - I2 - AT A TIME-)
      IND=1
      CALL BUFFERIN(ITAPE,1,IBUF(1,1),NWORDS,IND)
66    IF(IND.EQ.1)GO TO 66
62    GO TO(62,63,64,65)IND
63     WRITE(6,102)
102   FORMAT(1H1)
      DO 631 I=1,NW,NCHAN
      WRITE(6,104)(IBUF(J,1),J=I,I+NCHAN-1)
104    FORMAT(12O10)
631   CONTINUE
      GO TO 15
64     OUTPUT(101)-EOF READ-
      GO TO 15
65     OUTPUT(101)-READ ERR-
      GO TO 63
70    OUTPUT(101)-START ANALOG RECORDER-
      OUTPUT(101)-TYPE * C/R TO CONTINUE-
      INPUT(101)
      IND=1
      CALL BUFFERIN(ITAPE,1,IBUF,NWORDS,IND)
76    IF(IND.EQ.1)GO TO 76
71    GO TO(71,72,64,74)IND
72    DO 73 I=1,NWORDS
73    IBUF(I,1)=IBUF(I,1)/2**10
      DO 75 I=1,NWORDS,NCHAN
      DO 75 J=1,NCHAN
      CALL DAC(J,IBUF(I+J-1,1))
      N=NDEL
      CALL DELAY
75    CONTINUE
      GO TO 15
74    OUTPUT(101)-READ ERROR-
      GO TO 72
90    CALL DISABLE
      CALL ADSTOP
      OUTPUT(101)-RATE ERR-,RECNUM
      GO TO 15
      END
```

```
     SUBROUTINE PROCESS(IB,NS,NC,IS)
     DIMENSION IB(NC,NS),MEAN(10),SIGMA(10)
     REAL MEAN
     SCALE=100./2**23
     DO 1 I=1,10
 1   SIGMA(I)=MEAN(I)=0.
     DO 100 I=1,NC
     DO 10 J=1,NS
 10  MEAN(I)=MEAN(I)+SCALE*IB(I,J)
     MEAN(I)=MEAN(I)/NS
     DO 20 J=1,NS
 20  SIGMA(I)=SIGMA(I)+(MEAN(I)-IB(I,J)*SCALE)**2
     SIGMA(I)=SQRT(SIGMA(I)/NS)
     WRITE(6,1000)I,MEAN(I),SIGMA(I)
 1000 FORMAT($ CHAN $I2$  MEAN=$F8.4$  SIGMA=$F8.4/)
 100 CONTINUE
 30  IF(TEST(1).LT.0)GO TO 30
     IF(TEST(2).GT.0)RETURN
     RETURN IS
     END
¬META9300 SI,LO,GO
$ADSTART PZE
      BRM      9SETUPN
      PZE      6
NCH   PZE
BUF   PZE
NEWBUF PZE
MAXB  PZE
RECNUM PZE
NEXLOC PZE
      LDA      ENDBRM
      XMA      040
      STA      SV040
      LDA      INTBRM
      XMA      052
      STA      SV052
      LDA      *NCH
      STA      INCP
      ADD      =COMM
      COPY     (5,1)
      STA      COMLOC
      LDA      *NCH
      LLSA     15
      ADD      =COMM
      STA      0,1
      STA      CONTR
      LDA      *BUF
      STA      COMM
```

```
     LDA    *MAXB                144
     STA    MAX                  145
      SKR    NFULL               146
      BRU    $-1                 147
      EOM    034001              148
      POT    CONTR               149
      BRR    ADSTART             150
INTBRM BRM    ADFAST             151
ENDBRM BRM    ENDAD              152
SVC40 PZE                        153
ENDAD PZE                        154
      DIR                        155
      HLT                        156
      EOM    034001              157
      POT    CONTR               158
      EIR                        159
      BRC    *ENDAD              160
$ADSTOP PZE                      161
      LDA    SVC40               162
      STA    040                 163
      LDA    SV052               164
      STA    052                 165
      STZ    *COMLOC             166
      MPO    ADSTOP              167
      BRR    ADSTOP              168
COMLOC PZE                       169
$ADFAST PZE                      170
      DIR                        171
      STD    SVAB                172
      SKN    NFULL               173
      BRU    NXTBUF              174
      LDP    INCR                175
      ADD    COMM                176
      STA    COMM                177
      ADD    INCR                178
     SKL    MAX                  179
      STB    NFULL               180
      LDP    SVAB                181
      EIR                        182
      BRC    *ADFAST             183
NXTBUF LDA   *NEWBUF             184
      STA    COMM                185
      LDA    *MAXB               186
      STA    MAX                 187
      SKR    NFULL               188
      BRU    $-1                 189
      MPO   *RECNUM              190
      LDP    SVAB                191
```

```
        EIR
        BRC      *NEXLOC
COMM    RES      33
CONTR   PZE
MAX     PZE
SVAB    RES      2
INCR.   DATA     6,0
NFULL   PZE
SV052   PZE
        END
```

BIBLIOGRAPHY

1. A. B. Coppens and J.V. Sanders, "Finite-amplitude Standing Waves in Rigid-walled Tubes," J.Acoust. Sec. Am., V. 43, P. 516-529, March 1968.

2. A. B. Coppens and J. V. Sanders, Finite-amplitude Acoustic Processes in Ducts, paper presented at Applied Research Laboratories Conference, 5th, Austin, Texas, 10 November 1969.

3. Beech, W. L., Finite-amplitude Standing Waves in Rigid-Walled Tubes, M.S. Thesis, Naval Postgraduate School, Monterey, Calif., 1967.

4. G. Goertzel, "An Algorithm for the Evaluation of Finite Trigonometric Series," Amer. Math. Monthly, V. 65, P. 34-35, January 1958.

5. J. W. Cooley and J. W. Tukey, "An Algorithm for the Machine Calculation of Complex Fourier Series," Mathematics of Computations, V. 19, P. 297-303, April 1965.

6. Naval Postgraduate School Computer Facility Technical Note 0211-04, Procedures for Electrical Engineering Computer Laboratory Tapes and Fleet Numerical Weather Central Tapes, by P.C. Zeleny and R.D. Brunell, P. 1-5, April 1969.

7. Naval Postgraduate School Computer Facility Technical Note 0211-08, Procedures for Converting 7-Track Magnetic Tape to 9-Track Magnetic Tape, by S.D. Raney, P. 1-11, June 1970.

8. A. B. Coppens, personal communication.

INITIAL DISTRIBUTION LIST

		No. Copies
1.	Defense Documentation Center Cameron Station Alexandria, Virginia 22314	2
2.	Library, Code 0212 Naval Postgraduate School Monterey, California 93940	2
3.	Assoc. Professor James V. Sanders, Code 61Sd Department of Physics Naval Postgraduate School Monterey, California 93940	4
4.	Assoc. Professor Alan B. Coppens, Code 61Cz Department of Physics Naval Postgraduate School Monterey, California 93940	1
5.	James R. Winn 5050 Gola Dr. Wooster, Ohio 44691	1

UNCLASSIFIED

Security Classification

DOCUMENT CONTROL DATA - R & D

(Security classification of title, body of abstract and indexing annotation must be entered when the overall report is classified)

1 ORIGINATING ACTIVITY *(Corporate author)* Naval Postgraduate School Monterey, California 93940	2a. REPORT SECURITY CLASSIFICATION Unclassified 2b. GROUP

3 REPORT TITLE

FOURIER ANALYSIS OF EXPERIMENTAL FINITE-AMPLITUDE STANDING WAVES

4 DESCRIPTIVE NOTES *(Type of report and, inclusive dates)*

Master's Thesis; June 1971

5. AUTHOR(S) *(First name, middle initial, last name)*

James Richard Winn, Lieutenant, United States Navy

6. REPORT DATE	7a. TOTAL NO. OF PAGES	7b. NO. OF REFS
June 1971	53	8

8a. CONTRACT OR GRANT NO	9a. ORIGINATOR'S REPORT NUMBER(S)
b. PROJECT NO.	
c.	9b. OTHER REPORT NO(S) *(Any other numbers that may be assigned this report)*
d.	

10. DISTRIBUTION STATEMENT

Approved for public release; distribution unlimited.

11. SUPPLEMENTARY NOTES	12. SPONSORING MILITARY ACTIVITY Naval Postgraduate School Monterey, California 93940

13. ABSTRACT

Finite-amplitude standing waves in air at ambient conditions contained in a rigid-walled cylindrical tube with a large length-to-diameter ratio were experimentally investigated. The pressure waveform at the end of the tube was digitized and Fourier analyzed on an IBM 360 digital computer. Amplitudes and phases were obtained for all harmonics with amplitudes greater than 1% of the fundamental for strength parameters from 0.25 to 1.00 and for frequency parameters from -0.8 to 2.0. The strength and frequency parameters are defined as MbQ and $2\Delta f/\Delta f$ respectively, where M is the Mach number of fundamental, b the nonliniarity parameter, Q the quality factor of the resonator, Δf the frequency away from fundamental resonance, and Δf the band width at the half-power points. When these results are compared to the theoretical model of Coppens and Sanders, it is seen that while the theory accurately predicts the magnitude and shape of the harmonic content, it consistently underestimates the frequency at which each harmonic peaks. In addition, the theory fails to predict, except qualitatively, the phase angles.

DD FORM 1473 1 NOV 65 (PAGE 1)

S/N 0101-807-6811

UNCLASSIFIED

Security Classification

A-31[illegible]

KEY WORDS	LINK A		LINK B		LINK C	
	ROLE	WT	ROLE	WT	ROLE	WT
Finite-amplitude standing waves						
Strength parameter						
Frequency parameter						

14 AUG 78
24832

128443
Thesis
W6475 Winn
c.1
Fourier analysis of experimental finite-amplitude standing waves.

14 AUG 78
24832

Thesis
W6475 Winn
c.1
Fourier analysis of experimental finite-amplitude standing waves.
128443

thesW6475
Fourier analysis of experimental finite-
3 2768 001 89985 9
DUDLEY KNOX LIBRARY